

1J1001 4 to 1 BNC Converter



The 1J1001 4 to 1 BNC Converter is used to connect a Wayne Kerr 6500 analyzer to the Device Under Test using a single BNC connector. This is useful when the connection terminal of the DUT is a single BNC, such as some antennas. The outer of the single BNC is isolated.

Note that a customer-supplied balun will be required when the DUT is a balanced load

Suitable models

6500B series Precision Impedance Analyzer
6500P series HF LCR Meter

Specification

Frequency:	20 Hz to 120 MHz
Connection to Analyzer:	4-BNC 1 metre cable
Connection to DUT:	Single male BNC, outer isolated
Transfer Standards:	5-654-7015 Transfer Standard Box (supplied as standard) Contains Open, Short, 10 pF, 100 pF and 100 Ω standards